

GENERATOR SPECIFICATION	
Voltage	230/115
Phase	1
Frequency	50Hz
Prime Power (PRP)	3.4 kVA / 2.7 kW
Alternator	NSM K80C
Alternator Type	Brushless - Smooth Waveform
Fuel tank capacity	3.1 Litres
Autonomy 75% load	2.5 Hours
LWA	96
dBA @ 7M	71

ENGINE SPECIFICATION	
Engine	Honda GX200
Emissions certified	EU Stage V
Cylinders	Single
Distribution	O.H.V.
Aspiration	Naturally aspirated
Cooling	Air
Displacement	196 cm ³
Rpm	3000
Starting system	Recoil
Fuel	Unleaded 86 octane or higher



DIMENSIONS (mm)			WEIGHT (KG)
Length	Width	Height	
610	420	415	43



CONTROL BOX

- 115V: 1 x 16A & 1 x 32A BS4343 sockets.
- 230V: 2 x 16A BS4343 sockets.
- Reset circuit breaker overload protection.
- Voltage selector switch.

STANDARD FEATURES

- Robust metal control box.
- Oil alert/low oil shutdown.
- 3 Year engine warranty (Limited).
- Full wrap-around frame.
- Brushless smooth waveform alternator.

OPTIONS

- AVR (Automatic Voltage Regulator).
- LPG conversion.
- Long run tank (plastic).
- Single voltage.
- Trolley kit.



* Different model used to illustrate trolley option.

POWER DEFINITION

Prime Power (PRP) :

Applicable for supplying power to varying electrical load for unlimited hours in accordance ISO 8528-1.